



## **HOW TO STUN/KILL SHEEP AND GOATS ON-FARM**

Sheep and goats unable to be transported must be killed on-farm. They may also be killed on-farm for other reasons, such as illness or slow growth. Prior stunning is compulsory in all cases. Stun them to make them unconscious and **kill within 15 seconds** so that death is painless. Good handling and restraining are vital for effective stunning. This information does not override **national rules** that may forbid or restrict any of these practices.

Stunning and killing must be carried out by workers with an appropriate level of competence.

#### **ABOUT SHEEP AND GOATS**

- Sheep and goats are herd animals that like to stay in groups and get anxious when separated
- → Dairy sheep/goats are usually calm, but sheep/goats kept for meat/wool can be more anxious
- → Rams/bucks can be unpredictable and should be handled with care
- Nanny goats/ewes can get aggressive if split up from their kids/lambs
- Each sheep or goat can respond in a different way

# BEFORE STUNNING

#### Prepare the sheep or goat

- Make sure the animal's wool is dry
- Check the electrode pins are wet or alternatively, remove wool from the area where electrodes will be placed
- → Make sure the area where electrodes will be placed is wet
- Check the tongs are right size/not corroded
- Wear rubber gloves and boots

# **ELECTRICAL STUNNING/KILLING**

Once you have restrained the sheep or goat, the simplest method to kill them with electrical tongs is to first stun the head, followed by applying current on the heart (fibrillation).

### PHASE 1: **HEAD-ONLY STUNNING**

#### Place the electrodes


- → If using hand pliers: place the electrodes between corners of eyes and base of ears
- If using head-to-back handset: put handset between ears with electrodes on top of head
- Never place behind the ears





#### Check the positioning

Apply current that spans the heart on either side of chest, just behind front legs




## AFTER STUNNING

#### If the sheep or goat is still conscious:


- ♣ Don't apply the current on the heart (phase 2)
- → Stun it again in another position and with another device
- See what went wrong → Put it right before resuming stunning

Apply phase 2 within 15 seconds of stunning.



Minimum duration

head-only (seconds)



CONFIRM THE DEATH	
-------------------	--

#### Check for:

**Duration body stun** 

(seconds)

3

- No spontaneous movement
- → Limp/permanently collapsed body
- No response to pinch/prick on nose/ear
- No noise/panting
- No breathing
- Dilated pupils
- ♣ Bleeding stopped
- No heartbeat



Minimum voltage

(volts - V)

>150

RECOMMENDED PARAMETERS FOR ELECTRICAL STUNNING/KILLING

Frequency

(hertz - Hz)

50

Minimum current

(amperes - A)

1.0